

Historic of the 912-FA power supply units

	FA-101	FA-102	FA-202	FA-103	FA-203	FA-300	FA-310
912-MS	MS-101 MS-301 MS-302 MS-401 MS-402	MS-501 MS-502	MS-601 MS-602		MS-511 MS-512 MS-513 MS-514		
912-US	US-101 US-301 US-302 US-401 US-402	US-501 US-502	US-601 US-602		US-511 US-512 US-513 US-514		
912-UC				UC-102	UC-202 UC-212		UC-221 UC-222
912-TQ					TQ-501		TQ-511
912-TP						TP-521	TP-551 TP-561
905-TO							TO-551

	FA-101	FA-102	FA-202	FA-103	FA-203	FA-300	FA-310
	Cable 5 wires	Cable 5 wires	Cable 5 wires	Cable 5 wires	Cable 5 wires	Cable 5+1 wires	Cable 20 wires
Voltage	Masse	Masse	Masse	5 Vdc	5 Vdc	3,3 Vdc	3,3 Vdc
	5 Vdc	5 Vdc	5 Vdc	5 Vdc	5 Vdc	3,3 Vdc	5 Vdc
	12 Vdc	12 Vdc	12 Vdc	13 Vdc	13 Vdc	3,3 Vdc	12 Vdc
	18 Vdc	18 Vdc	18 Vdc	13 Vdc	13 Vdc	5 Vdc	24 Vdc
	30 Vdc	30 Vdc	30 Vdc	30 Vdc	30 Vdc	12 Vdc	
						24 Vdc	

All power supply units have a mass connection through the chassis

Exchanging the power supply from a system

Depending on the actual power supply

MODÈLE	FA-101	FA-102	FA-202	FA-103	FA-203	FA-300	FA-310
FA-101	YES	YES	YES				
FA-102	YES	YES	YES				
FA-202	YES	YES	YES				
FA-103				YES	YES		
FA-203				YES	YES		
FA-300						YES	
FA-310							YES

Adding a module to a system

Depending on the power supply of the actual system

		FA-101	FA-102	FA-202	FA-103	FA-203	FA-300	FA-310
912-MS	MS-101 MS-301 MS-302 MS-401 MS-402	YES	YES	YES				
	MS-501 MS-502	YES	YES	YES				
	MS-601 MS-602	YES	YES	YES				
	MS-511 MS-512 MS-513 MS-514	LA-001	LA-001	LA-001	YES	YES		
912-US	US-101 US-301 US-302 US-401 US-402	YES	YES	YES				
	US-501 US-502	YES	YES	YES				
	US-601 US-602	YES	YES	YES				
	US-511 US-512 US-513 US-514	LA-001	LA-001	LA-001	YES	YES		
912-UC	UC-102				YES	YES		
	UC-202 UC-212				YES	YES		
	UC-221 UC-222							YES
	TQ-501 TQ-511				YES	YES		YES
912-TP	TP-521						YES	
	TP-551 TP-561							YES
905-TO	TO-551							YES
905-ZG		CA-024	CA-024	CA-024	CA-025	CA-025		
905-ZP		CA-024	CA-024	CA-024	CA-025	CA-025		